

## CENTRALINA 100V A 10 ZONE

Zone system

Reference: ZSC-1110



100 V Zone system Features: Switching and control of 10 loudspeaker zones, expandable to 300 zones. Possibility of paging using the microphone with zone selector mod. ZS-11. Up to 16 microphones can be connected with zone selector mod. ZS-11. 2 100 V line inputs for each zone, to connect the background music and paging amplifiers, general purpose inputs and outputs for connection to the alarm centre, line inputs and microphone inputs. Applications: For commercial installations that require different audio for each of the zones. Technical data: Inputs: 2 unbalanced mics, 6.3 mm jack 2 unbalanced lines, euroblock 2 contact closure alarm activation, euroblock 10 x 100 V lines for paging amplifier, 500 W maximum, euroblock 10 x 100 V lines for background music amplifier, 500 W maximum, euroblock 1 mic with zone selector, RJ45 Departures: 10 loudspeaker zones, euroblock 2 unbalanced lines, euroblock 2 alarms for contact closure, euroblock 1 zone extension, RJ45

Peso netto	5.00
Larghezza	48.400
Altezza	8.800
Profondità	34.000