

AMPLIFICATORE A MATRICE 5 IN / 4OUT - 4 X 90W

Multi-zone amplifier

Reference: MPZ-461



Multi-zone matrix amplifier Features: 5 input channels and USB/SD/MP3 player with FM radio that can be assigned to any of the 4 output zones. The input channels have gain, bass, treble and volume controls. Output zones have independent volume and line output control. Paging is possible using the microphone with zone selector mod. M-46 (up to 4 microphones can be connected). Selectable phantom power, priority paging and paging tones with volume control. The temperature, overload and short-circuit protection circuits ensure high reliability. Includes remote control for the USB/SD/MP3/FM player. Easy installation and intuitive use. Applications: For commercial installations that require different audio for each zone. Technical data: 4 x 90 W RMS Inputs: 3 balanced mics/lines, combo (XLR and 6.3 mm jack), switchable 2 aux, 2 x RCA 1 tel. paging, screw terminals 1 microphone with zone selector, RJ-45 Outputs: 4 balanced or unbalanced lines, zones 1 to 4, screw terminals, 1 monitor, screw terminals 1 W 8 Ohm

Peso netto	15.82
Larghezza	44.000
Altezza	13.800
Profondità	48.300