

Power amplifier

Power amplifier

Reference: SA-1208



Power amplifier BENEFITS The SA series power amplifiers offer great power and sound quality with high performance and stability. Operating and power modes: Stereo and parallel: up to 1,500 + 1,500 W RMS at 2 Ohm. Bridge: up to 1,600 W RMS at 8 Ohm High reliability with: soft start, forced ventilation with variable speed and protection circuits (temperature, short circuit, overload, DC and AC). Audio inputs with market standard connections: XLR and 6.3 mm jack and volume control for each channel. Speaker outputs with screw terminals and banana plugs or speaker connector. Very easy to use and minimum setup time. **APPLICATIONS** Designed for professional use in different itinerant events such as discos, concerts, festivals, meetings, etc. as well as for fixed installations in nightclubs, pubs, auditoriums, etc. **TECHNICAL DATA** Response: 10-50,000 Hz, (-1.5 dB) Harmonic distortion: 500 S/N ratio: > 103 dB Crosstalk: > 105 dB Rate of change: 70 V/ μ s

Peso netto	17.60
Larghezza	48.300
Altezza	8.900
Profondità	48.000